



# 400 Watt Modified Sinewave Inverter

## Specifications

AC OUTPUT	
Power (Continuous)	400W
Power (Peak)	800W
Voltage	120Vac
Current	3.3A
Frequency	60±1Hz
Waveform	Modified Sinewave
DC INPUT	
Voltage (nominal)	12.5Vdc
Operation Range	10.5 -15.5Vdc
Current	38A
PROTECTION	
Input Undervoltage Warning	11.0±0.3Vdc
Input Undervoltage Shutdown	1 0.5±0.3Vdc
Input Undervoltage Recovery	12.0±0.3Vdc
Input Overvoltage Shutdown	15.5Vdc
Overvoltage Shutdown	Yes
Overload Shutdown	Yes
Output Short circuit Shutdown	Yes
Over Temperature Shutdown	Yes



### USE IT TO POWER

laptops, cell phones, TV's DVD players, lights and small power tools whenever you need them

### USE IT IN YOUR CAR

To recharge cellular phone and MP3's



### USE IT IN THE RV

To run TV's and lights



### USE IT ON THE BOAT

To run computers and small power too



## ESTIMATED AC LOAD RUN-TIME WITH VARIOUS BATTERIES

AC Load Power	12V - 40AH	12V - 60AH	12V -120AH	12V -180AH
20W	13.5 hrs	22 hrs	44 hrs	66 hrs
40W	8 hrs	12 hrs	27 hrs	41 hrs
50W	6.5 hrs	11 hrs	22 hrs	33 hrs
100W	3 hrs	5 hrs	11.5 hrs	17 hrs
150W	2 hrs	3.5 hrs	7 hrs	12 hrs
200W	1.5 hrs	2.5 hrs	5 hrs	8 hrs
300W	47 min	1 hrs	3 hrs	4.5 hrs

## Shipping Details

Item Number:	38204
UPC Code:	839290003077
Country of Origin:	China
Shipping Dimensions:	206 x 24 x 260 mm
Shipping Weight:	1.05 Kg
Master Quantity:	10
Master Dimensions:	48.2 x 36.8 x 28.5 cm
Master Weight:	12.1 Kg

DC to AC Power Inverter Convert Battery Power to Household AC Power

