



Features

Convert battery power to household AC power installation.

- 2 x AC Outlets Allow You to Run Multiple Devices at The Same Time
- Runs Home Appliance, TVs , Power Tools and More
- Comes With Battery Clamps Cable.
- 400 Watt Continuous Output, 800 Watts Surge
- Compact Size



SPECIFICATIONS

AC OUTPUT

Power: 400W (Continuous), 800W(Peak)

Voltage / Current: 120 Vac / 3.3A

Frequency: 60±1Hz

Waveform: Modified sinewave

AC Outlet: 2 x 3Prong GFCI AC outlet

DC INPUT

Voltage (nominal): 12.8-13.2Vdc

Operation Range: 10.5-15.5Vdc / 38A

Material: ABS, Stell, Aluminum

PROTECTION:

Input Undervoltage Warning: 11.0±0.3Vdc

Input Undervoltage Shutdown: 10.5±0.3Vdc

Input Undervoltage Recovery: 12.0±0.3Vdc

Input Overvoltage Shutdown: 15.5Vdc

Overload Shutdown: Yes

Output Short circuit Protection: Yes

Over Temperature Shutdown: Yes

SHIPPING DETAILS

Item Number: 38204

UPC Code: 839290003077

Country of Origin: China / Hong Kong

Product Dims LxWxH: 6.5 x 4.2 x 2 in

Blister Box Dims LxWxH: 10 x 9.7 x 3.8 in

Product Weight: 2.3 lbs with package

2.1 lbs without package

Master Quantity: -

Master Dimensions: - in

Master Weight: - lbs



1-800-588-0590

www.naturepowerproducts.com



fb.me/NaturePowerProducts

