



H

L

W

## Features

*Convert battery power to household AC power installation.*

- **2 x AC Outlets Allow You to Run Multiple Devices at The Same Time**
- **Runs Home Appliance, TVs , Power Tools and More**
- **Ideal For RVs, Boats, Trucks and Cabins**
- **USB Outlet Charges Tablets, Phones and Most Portable Electronics**
- **2000 Watt Continuous Output, 4000 Watts Surge**
- **Compact Size**



## SPECIFICATIONS

### AC OUTPUT

**Power:** 2000W (Continuous), 4000W(Peak)

**Voltage / Current:** 120 Vac / 16.6A

**Frequency:** 60±1Hz

**Waveform:** Pure Sinewave

**AC Outlet:** 2 x 3Prong GFCI AC outlet

### DC OUTPUT

**USB:** 1 x 5V/750mA

### DC INPUT

**Voltage (nominal):** 12.5Vdc

**Operation Range:** 10.5-15.5Vdc / 180A

**Material:** ABS, Stell, Aluminum

### PROTECTION:

**Input Undervoltage Warning:** 11.0±0.3Vdc

**Input Undervoltage Shutdown:** 10.5±0.3Vdc

**Input Undervoltage Recovery:** 12.0±0.3Vdc

**Input Overvoltage Shutdown:** 15.5Vdc

**Overload Shutdown:** Yes

**Output Short circuit Protection:** Yes

**Over Temperature Shutdown:** Yes

## SHIPPING DETAILS

Item Number: 38320

UPC Code: 839290003107

Country of Origin: China / Hong Kong

Product Dims LxWxH: 16.5 x 9 x 4.5 in

Color box Dims LxWxH: 19 x 11.1 x 6.8 in

Product Weight: 13.2 lbs with package

11.7 lbs without package

Master Quantity: -

Master Dimensions: - in

Master Weight: - lbs



**1-800-588-0590**

[www.naturepowerproducts.com](http://www.naturepowerproducts.com)



[fb.me/NaturePowerProducts](https://fb.me/NaturePowerProducts)

