



Features

Convert battery power to household AC power installation.

- 2 x AC Outlets Allow You to Run Multiple Devices at The Same Time
- Runs Home Appliance, TVs , Power Tools and More
- Ideal For RVs, Boats, Trucks and Cabins
- USB Outlet Charges Tablets, Phones and Most Portable Electronics
- 1000 Watt Continuous Output, 2000 Watts Surge
- Compact Size



SPECIFICATIONS

AC OUTPUT

Power: 1000W (Continuous), 2000W(Peak)

Voltage / Current: 120 Vac / 8.3A

Frequency: 60±1Hz

Waveform: Pure Sinewave

AC Outlet: 2 x 3Prong GFCI AC outlet

DC OUTPUT

USB: 1 x 5V/750mA

DC INPUT

Voltage (nominal): 12.5Vdc

Operation Range: 10.5-15.5Vdc / 94A

Material: ABS, Stell, Aluminum

PROTECTION:

Input Undervoltage Warning: 11.0±0.3Vdc

Input Undervoltage Shutdown: 10.5±0.3Vdc

Input Undervoltage Recovery: 12.0±0.3Vdc

Input Overvoltage Shutdown: 15.5Vdc

Overload Shutdown: Yes

Output Short circuit Protection: Yes

Over Temperature Shutdown: Yes

SHIPPING DETAILS

Item Number: 38310

UPC Code: 839290003091

Country of Origin: China / Hong Kong

Product Dimensions: 12.3 x 6.9 x 3.4 in

Color box Dimensions: 15.4 x 8.9 x 5.5 in

Product Weight: - lbs with package

- lbs without package

Master Quantity: -

Master Dimensions: - in

Master Weight: - lbs



1-800-588-0590

www.naturepowerproducts.com



fb.me/NaturePowerProducts

