



Battery clamp-O ring bare end 10AWG, 3.3ft      12V Car Plug-O ring bare end 16AWG, 3.3ft

## Features

Convert battery power to household AC power installation.

- 2 x AC Outlets Allow You to Run Multiple Devices at The Same Time
- Runs Microwave Ovens, Computers, Power Tools and More
- Comes With Battery Clamps Cable.
- USB Outlet Charges Tablets, Phones and Most Portable Electronics
- 400 Watt Continuous Output, 800 Watts Surge
- Compact Size



## SPECIFICATIONS

<b>AC OUTPUT</b>
Power: 400W (Continuous), 800W(Peak)
Voltage / Current: 120 Vac / 12.5A
Frequency: 60Hz
Waveform: Pure Sinewave
AC Outlet: 2 x 3Prong GFCI AC outlet
<b>DC OUTPUT</b>
USB: 1 x 5V/2.1A
<b>DC INPUT</b>
Voltage (nominal): 12Vdc
Operation Range: 10.5-15.5Vdc / 38A
Material: ABS, Stell, Aluminum
<b>PROTECTION:</b>
Input Undervoltage Warning: 11.0Vdc
Input Undervoltage Shutdown: 10.5Vdc
Input Undervoltage Recovery: 12.0Vdc
Input Overvoltage Shutdown: 15.75Vdc
Overload Shutdown: Yes
Output Short circuit Protection: Yes
Over Temperature Shutdown: Yes

## SHIPPING DETAILS

Item Number: 38304
UPC Code: 839290003084
Country of Origin: China / Hong Kong
Product Dims LxWxH: 7.8 x 7 x 3.3 in
Color box Dims LxWxH: 10.88 x 8.91 x 5.75 in
Product Weight: 5.2 lbs with package 4.4 lbs without package
Master Quantity: -
Master Dimensions: - in
Master Weight: - lbs



**1-800-588-0590**

[www.naturepowerproducts.com](http://www.naturepowerproducts.com)

[fb.me/NaturePowerProducts](https://fb.me/NaturePowerProducts)

