



# 2000 Watt Sinewave Inverter



## Specifications

AC OUTPUT	
Power (Continuous)	2000W
Power (Peak)	4000W
Voltage	120Vac
Current	16.6A
Frequency	60±1Hz
Waveform	True Sinewave
DC OUTPUT	
5V USB	750mA
DC INPUT	
Voltage (nominal)	12.5Vdc
Operation Range	10.5 -15.5Vdc
Current	180A
DISPLAY	
LED Indicator	Yes
PROTECTION	
Input Undervoltage Warning	11.0±0.3Vdc
Input Undervoltage Shutdown	10.5±0.3Vdc
Input Undervoltage Recovery	12.0±0.3Vdc
Input Overvoltage Shutdown	15.5Vdc
Output Power Shutdown	Yes
Output Short Circuit	Yes
Temperature Warning	Yes
Temperature Shutdown	Yes

### USE IT TO POWER

laptops, cell phones, TV's DVD players, lights and small power tools whenever you need them

### USE IT IN YOUR CAR

To recharge cellular phone and MP3's



### USE IT IN THE RV

To run TV's and lights



### USE IT ON THE BOAT

To run computers and small power too



## ESTIMATED AC LOAD RUN-TIME WITH VARIOUS BATTERIES

AC Load Power	12V - 40AH	12V - 60AH	12V -180AH	12V -240AH	12V -240AH
40W	8 hrs	27 hrs	41 hrs	54 hrs	68 hrs
50W	6.5 hrs	22 hrs	33 hrs	44 hrs	55 hrs
100W	3 hrs	11.5 hrs	17 hrs	23 hrs	29 hrs
150W	2 hrs	7 hrs	12 hrs	14 hrs	20 hrs
200W	1.5 hrs	5 hrs	8 hrs	11 hrs	13.5 hrs
350W	47 mins	3 hrs	4.5 hrs	6 hrs	7.5 hrs
500W	26 mins	2 hrs	3 hrs	4 hrs	5 hrs
1000W	8 mins	49 mins	1.5 hrs	2 hrs	2.5 hrs
1500W	N/A	27 min	49 mins	1 hr	1.5 hrs
2000W	N/A	20 min	41 mins	54 mins	1 hrs

## Shipping Details

Item Number:	38320
UPC Code:	839290003107
Country of Origin:	China
Shipping Dimensions:	19.1 X 11.3 X 6.8 in
Shipping Weight:	11.5 lbs
Master Quantity:	3
Master Dimensions:	19.7 x 11.8 x 21.7 in
Master Weight:	41.1 lbs

**DC to AC Power Inverter**  
Convert Battery Power to Household AC Power

