



# NATURE POWER 150 WATT POWER INVERTER



Connecting Cable with 12V Car plug

## Features

Convert battery power to household AC power installation.

- 1 x AC Outlet Charging Computers, Runs Fan, Small Power Tools and More
- 2 Amp USB Outlet Charges Tablets, Phones and Most Portable Electronics
- 150 Watt Continuous Output, 300 Watts Surge
- Compact – Easily Stores in any Vehicle or Purse



## SPECIFICATIONS

### AC OUTPUT

Power: 150W (Continuous), 300W(Peak)

Voltage: 115±10 Vac

Frequency: 60±3

Waveform: Modified sinewave

AC Outlet: 1 x 3Prong AC outlet

### DC OUTPUT

USB: 1 x 5V/2A

### DC INPUT

Voltage (nominal): 12.8-13.2Vdc

Operation Range: 10.0-15.0Vdc

Material: ABS, Stell

### PROTECTION:

Input Undervoltage Shutdown/Warning: 10.0±0.5Vdc

Input Undervoltage Recovery: 12.0±0.5Vdc

Input Overvoltage Shutdown: 15.5±0.5Vdc

Overload Shutdown: Yes

Output Short circuit Protection: Yes

Over Temperature Shutdown: Yes

## SHIPPING DETAILS

Item Number: 37150

UPC Code: 839290003015

Country of Origin: China / Taiwan

Product Dims LxWxH: 2.5 x 2.3 x 5.5 in

Color box Dims LxWxH: 3.1 x 2.6 x 7.1 in

Product Weight: 0.7 lbs with package

0.6 lbs without package

Master Quantity: -

Master Dimensions: - in

Master Weight: - lbs



1-800-588-0590

[www.naturepowerproducts.com](http://www.naturepowerproducts.com)



[fb.me/NaturePowerProducts](https://fb.me/NaturePowerProducts)

