



NATURE POWER 300 WATT POWER INVERTER



Features

Convert battery power to household AC power installation.

- 2 x AC Outlets Allow You to Run Multiple Devices at The Same Time
- Runs Home Appliance, TVs , Power Tools and More
- Comes With Both DC Plug and Battery Clamps
- 300 Watt Continuous Output, 600 Watts Surge
- Compact Size



SPECIFICATIONS

AC OUTPUT

Power: 300W (Continuous), 600W(Peak)

Voltage: 115±10 Vac

Frequency: 60±3

Waveform: Modified sinewave

AC Outlet: 2 x 3Prong AC outlet

DC OUTPUT

USB: 1 x 5V/2A

DC INPUT

Voltage (nominal): 12.8-13.2Vdc

Operation Range: 10.0-15.0Vdc

Material: ABS, Stell, Aluminum

PROTECTION:

Input Undervoltage Shutdown/Warning: 10.0±0.5Vdc

Input Undervoltage Recovery: 12.0±0.5Vdc

Input Overvoltage Shutdown: 15.5±0.5Vdc

Overload Shutdown: Yes

Output Short circuit Protection: Yes

Over Temperature Shutdown: Yes

SHIPPING DETAILS

Item Number: 37300

UPC Code: 839290003305

Country of Origin: China / Taiwan

Product Dims LxWxH: 6.2 x 3.5 x 2.2 in

Color box Dims LxWxH: 6.8 x 2.3 x 5.2 in

Product Weight: 1.6 lbs with package

1.45 lbs without package

Master Quantity: -

Master Dimensions: - in

Master Weight: - lbs



1-800-588-0590

www.naturepowerproducts.com



fb.me/NaturePowerProducts

