



# NATURE POWER 300 WATT PURE SINE WAVE POWER INVERTER



Battery Cable  
7AWG, 2x39.3"

## Features

Convert battery power to household AC power

- Pure Sine Wave, Highest Quality Power For All Kinds Of Power Device ( Not Including Medical Equipment)
- 2 x AC Outlets Allow You to Run Multiple Devices at The Same Time
- Runs Home Appliance, TVs , Power Tools and More
- 300 Watts Continuous Output, 600 Watts Surge
- Comes With Battery Connect Cables
- Compact Size



## SPECIFICATIONS

### AC OUTPUT

Power: 300W (Continuous), 600W(Peak)

Voltage: 115±10% Vac

Frequency: 60±3 Hz

Waveform: Pure sinewave

AC Outlet: 2 x 3Prong AC outlet

### DC OUTPUT

USB: 1 x 5V/2A

### DC INPUT

Voltage (nominal): 12.8-13.2Vdc

Operation Range: 10.0-15.0Vdc

Material: ABS, Stell, Aluminum

### PROTECTION:

Input Undervoltage Warning: 10.5±0.5Vdc

Input Undervoltage Shutdown: 10.0±0.5Vdc

Input Overvoltage Shutdown: 15.5±0.5Vdc

Overload Shutdown: Yes

Output Short circuit Protection: Yes

Over Temperature Shutdown: Yes

## SHIPPING DETAILS

Item Number: 38300

UPC Code: 839290003343

Original: Taiwan

Product Dims LxWxH: 6.7 x 4.1 x 2.2 in

Color box Dims LxWxH: 7.3 x 5.9 x 2.2 in

Product Weight: 2.2 lbs with package

1.5 lbs without package

Master Quantity: 20

Master Dimensions: 16.1 x 13.4 x 13 in

Master Weight: 44 lbs



1-800-588-0590

[www.naturepowerproducts.com](http://www.naturepowerproducts.com)



[fb.me/NaturePowerProducts](https://fb.me/NaturePowerProducts)

